

ARISTA

Audit Logs Message Guide

CloudVision

April 2026

Arista Networks



[Arista.com](https://www.arista.com)

Headquarters	Support	Sales
5453 Great America Parkway Santa Clara, CA 95054 USA +1-408-547-5500	+1-408-547-5502 +1-866-476-0000	+1-408-547-5501 +1-866-497-0000
www.arista.com/en/	support@arista.com	sales@arista.com

© Copyright 2026 Arista Networks, Inc. All rights reserved. The information contained herein is subject to change without notice. The trademarks, logos, and service marks ("Marks") displayed in this documentation are the property of Arista Networks in the United States and other countries. Use of the Marks is subject to the Arista Networks Terms of Use Policy, available at www.arista.com/en/terms-of-use. Use of marks belonging to other parties is for informational purposes only.

Contents

1 Syslog Message overview	4
1.1 Message Format	4
1.2 Severity Levels	5
2 Audit Log Messages	6
2.1 A	6
2.2 C	10
2.3 D	31
2.4 F	35
2.5 I	36
2.6 L	45
2.7 M	50
2.8 O	53
2.9 P	54
2.10 R	55
2.11 S	57
2.12 U	60

Chapter 1

Syslog Message overview

1.1 Message Format

Syslog Messages have the following format structure:

facility: severity: timestamp hostname service mnemonic Message: messageText, User: userName[, DeviceName: deviceName]

Here's an explanation of each of the fields in the syslog message:

facility	Source or system area that generated the message.
severity	Level of importance or urgency of the syslog message.
timestamp	Time at which the alog is written in aeris.
hostname	Hostname of the node for which syslog is sent.
service	Service name for which alog is added.
mnemonic	This is a mnemonic code that uniquely identifies the message. Mnemonic codes are all upper case character strings.
messageText	Message in the audit log.
userName	CloudVision logged in user for which alog is created.
deviceName	Device for which logs are added.

*fields inside [] are optional, may or may not be present in the syslog message.

1.2 Severity Levels

The severity of a system message varies from -1 to 7. The lower the severity, the higher the criticality of the message. The different severity levels are described below.

Severity	Description
-1	Emergency - the system cannot be used. Immediate administrator attention is required.
1	Alert - the system has encountered an alert. The message details help describe the urgency.
2	Critical - the system has encountered a critical error. The message details help describe the urgency.
3	Error - the system has encountered an error. The message details help describe the urgency.
4	Warning - something may be wrong, or misconfigured. No immediate attention is required, although further investigation is required.
5	Notice - not used. We generally use severity level Info instead.
6	Info - informational message about the system. Provides changes in operational status.
7	Debug - used for aiding in troubleshooting. This could produce excessive output and should not be used without discussing with your technical support representative.

Chapter 2

Audit Log Messages

Mnemonic: AAA_RATE_LIMITER_DEF_UPDATED

Message: Login API rate limit updated by <userName>, to <rateLimiterInfo>

Severity: Info

Explanation: Login API rate limit updated successfully

Recommended Action: No action required

Services: aaa

Mnemonic: AAA_RATE_LIMITER_EXCEEDED

Message: Login API rate limit exceeded for user <userName> with IP <IPAddress>

Severity: Error

Explanation: Login API rate limit exceeded

Recommended Action: Please wait for sometime before trying again. Contact network admin for exact rate limits configured. If the problem persists, contact Arista support

Services: aaa

Mnemonic: AAA_SERVER_AUTH_SETTINGS_UPDATED

Message: AAA settings updated for <settingsKey>

Severity: Info

Explanation: AAA auth settings are updated successfully

Recommended Action: No action required

Services: aaa

Mnemonic: AAA_SERVER_SETTINGS_ADDED

Message: AAA server settings added for <IPAddress>

Severity: Info

Explanation: AAA server settings are added successfully

Recommended Action: No action required

Services: aaa

Mnemonic: AAA_SERVER_SETTINGS_DELETED

Message: AAA server settings deleted for <server>
Severity: Info
Explanation: AAA server settings are deleted successfully
Recommended Action: No action required
Services: aaa

Mnemonic: AAA_SERVER_SETTINGS_UPDATED
Message: AAA server settings updated for <IPAddress>
Severity: Info
Explanation: AAA server settings are updated successfully
Recommended Action: No action required
Services: aaa

Mnemonic: AAA_SETTINGS_UPDATED
Message: AAA settings successfully updated to: <updatedSettings>
Severity: Info
Explanation: AAA settings updated successfully.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: ACCESS_PRIVILEGE_DEV_PERM_UPDATED
Message: Successfully updated device permissions for access privilege <accessPrivilegeName>
Severity: Info
Explanation: Successfully updated device permissions for the access privilege.
Recommended Action: No action required
Services: device-rbac

Mnemonic: ACCESS_PRIVILEGE_DEV_PERM_UPDATE_FAILED
Message: Failed to update or create device permission for access privilege <accessPrivilegeName>.
Severity: Critical
Explanation: Update of device permissions for an access privilege failed.
Recommended Action: Try updating the access privilege again
Services: device-rbac

Mnemonic: ACTION_CREATED

Message: Action <actionName> starting for user <userName>

Severity: Info

Explanation: Action has started

Recommended Action: No action required

Services: execaction

Mnemonic: ACTION_CREATED_WITH_DEVICE

Message: Action <actionName> starting for user <userName> on device <deviceKey>

Severity: Info

Explanation: Action has started

Recommended Action: No action required

Services: execaction

Mnemonic: ADD_DEVICE

Message: Device <deviceID> added successfully

Severity: Info

Explanation: Device successfully added

Recommended Action: No action required

Services: admin-aaa

Mnemonic: ADD_ENROLLMENT_TOKEN

Message: Enrollment token successfully added

Severity: Info

Explanation: Enrollment token successfully added

Recommended Action: No action required

Services: admin-aaa

Mnemonic: ADD_RELATION

Message: Entity: <entityID> of EntityType: <entityType>, added relations: <relations> for subject: <subjectID> of subjectType: <subjectType>, on object: <objectID> of objectType: <objectType>

Severity: Info

Explanation: Added access control relations.

Recommended Action: No action required

Services: accesscontrol

Mnemonic: ARISTA_PORTAL_PROXY_DELETE_SUCCESS

Message: User <userName> deleted an arista portal proxy at time <timestamp>

Severity: Info

Explanation: A user deleted an arista portal proxy at the given time.

Recommended Action: No action required

Services: aristaportal

Mnemonic: ARISTA_PORTAL_PROXY_WRITE_SUCCESS

Message: User <userName> added an arista portal proxy at time <timestamp>

Severity: Info

Explanation: A user added an arista portal proxy at the given time.

Recommended Action: No action required

Services: aristaportal

Mnemonic: ARISTA_PORTAL_TOKEN_DELETE_SUCCESS

Message: User <userName> deleted an arista portal token at time <timestamp>

Severity: Info

Explanation: A user deleted an arista portal token attribute at the given time.

Recommended Action: No action required

Services: aristaportal

Mnemonic: ARISTA_PORTAL_TOKEN_WRITE_SUCCESS

Message: User <userName> added an arista portal token at time <timestamp>

Severity: Info

Explanation: A user added an arista portal token attribute at the given time.

Recommended Action: No action required

Services: aristaportal

Mnemonic: CA_ROTATION_FAILED

Message: CA rotation failed

Severity: Error

Explanation: CA rotation failed.

Recommended Action: Please check the failure reason and optionally retry. Contact Arista support if the problem persists.

Services: camanager

Mnemonic: CA_ROTATION_INITIATED

Message: CA rotation started

Severity: Info

Explanation: CA rotation has started. This will generate new CA and signed certificates.

Recommended Action: No action required

Services: camanager

Mnemonic: CA_ROTATION_SUCCESS

Message: CA rotation successful

Severity: Info

Explanation: CA rotation has completed successfully.

Recommended Action: No action required

Services: camanager

Mnemonic: CC_ACTION_COMPLETED

Message: Action <actionName> completed successfully

Severity: Info

Explanation: Action has completed

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_ACTION_STARTED

Message: Action <actionName> started

Severity: Info

Explanation: Action has started

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_DEVICE_SUCCEEDED

Message: Checking device status succeeded

Severity: Info

Explanation: Checking device status succeeded.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_INTERFACE_STARTED

Message: Checking interfaces status started

Severity: Info

Explanation: Checking interfaces status started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_INTERFACE_SUCCEEDED

Message: Checking interfaces status succeeded

Severity: Info

Explanation: Checking interfaces status succeeded.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_PEER_STARTED

Message: Checking BGP peer(s) status started

Severity: Info

Explanation: Checking BGP peer(s) status started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_PEER_SUCCEEDED

Message: Checking BGP peer(s) status succeeded

Severity: Info

Explanation: Checking BGP peer(s) status succeeded.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_VRF_CONVERGENCE_STARTED

Message: Checking BGP convergence on all VRFs started
Severity: Info
Explanation: Checking BGP convergence on all VRFs started.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CHECK_VRF_CONVERGENCE_SUCCEEDED
Message: Checking BGP convergence of all VRFs succeeded
Severity: Info
Explanation: Checking BGP convergence of all VRFs succeeded.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_COMPLIANCE_CHECK_FAILED
Message: Compliance check for device <hostname> failed, error: <error>
Severity: Info
Explanation: Compliance check for device failed.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_COMPLIANCE_CHECK_SUCCEEDED
Message: Compliance check for device <hostname> succeeded
Severity: Info
Explanation: Compliance check for device succeeded.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CONNECTED_INTERFACES_PUBLISHED
Message: Published connected interfaces to database successfully
Severity: Info
Explanation: Published connected interfaces successfully.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_CONVERGENCE_HEALTH_FAILED
Message: Checking BGP convergence of all VRFs every <pollInterval>, attempt

<attemptNumber> failed error: <error>

Severity: Error

Explanation: Internal error when checking the convergence.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_DEVICE_STATUS_STARTED

Message: Checking device status started

Severity: Info

Explanation: Checking device status started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_INTERFACE_STATUS_FAILED

Message: Checking interfaces status every <pollInterval>, attempt <attemptNumber> failed error: <error>

Severity: Error

Explanation: Internal error while getting the interface status.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_MAINT_HEALTH_FAILED

Message: Checking device health every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Error

Explanation: Internal error while checking the device health.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_PEER_MAINT_HEALTH_FAILED

Message: Checking BGP peer(s) health every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Error

Explanation: Internal error while checking the peer's health.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_READ_SUCCEEDED

Message: Read maintenance section from running-config successfully: <maintenanceSection>

Severity: Info

Explanation: Read maintenance section from running-config successfully.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_BGPMAINTMODE_STARTED

Message: Executing <actionName> for device: <hostname>

Severity: Info

Explanation: Enter or exit bgp maint mode started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CLEANFLASH_STARTED

Message: Cleaning up files matching the criteria: <fileSpecification> from <deviceId>

Severity: Info

Explanation: ChangeControl Cleanflash action started

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_COMMAND_RUN

Message: Command(s) "<command(s)>" execution succeeded, response from device (<deviceId>): <commandResponse(s)>.

Severity: Info

Explanation: Commands run on the device and response from device

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_COMPLETED

Message: CC <ccName> completed successfully

Severity: Info

Explanation: CC completed successfully

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CONFIG_ABANDON_DELTA_PUSH

Message: Failed to apply delta config, falling back to replacing with session configuration

Severity: Error

Explanation: Delta Push failed - Switching to regular config push

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CONFIG_ABORT_AND_RESTORE

Message: Aborted change and reverted to previous configuration

Severity: Error

Explanation: Config session aborted and restored to old config

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_CONFIG_COMMIT

Message: Committing configuration with a timer of <commitTimerSeconds> seconds

Severity: Info

Explanation: Committing configuration for device with timer

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CONFIG_COMPLIANCE_CHECK_FAILED

Message: Error while updating compliance code: <error>

Severity: Error

Explanation: Error while updating compliance code

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_CONFIG_COMPLIANT

Message: The config of the device <hostName> is in compliance

Severity: Info

Explanation: The config of the device is in compliance.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CONFIG_NON_COMPLIANT

Message: The config of the device <hostName> is not in compliance

Severity: Info

Explanation: The config of the device is not in compliance.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CONFIG_PUSH

Message: Applying new configuration

Severity: Info

Explanation: Replacing configuration on the device.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_CONFIG_STARTED

Message: Applying <configSource> at the timestamp <configTimestamp> on <hostname>

Severity: Info

Explanation: ChangeControl Set Config action started

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_DEVICE_ACTION_COMPLETED

Message: Action <actionName> on device <deviceId> completed successfully

Severity: Info

Explanation: Action has completed

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_DEVICE_ACTION_STARTED

Message: Action <actionName> on device <deviceId> started

Severity: Info

Explanation: Action has started

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_DOWNLOADFILE_STARTED

Message: Attempting to download <sourceUrl> to <deviceId>

Severity: Info
Explanation: ChangeControl Download file action started
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_ENTERZTP_DEVICE_IN_ZTP
Message: Device <deviceID> is already in ZTP mode before action started
Severity: Info
Explanation: Device is already in ZTP mode, so cannot perform EnterZTP action
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_ENTERZTP_ERASING_CONFIG
Message: Erasing configuration for device <deviceID>
Severity: Info
Explanation: Device configuration is being erased.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_ENTERZTP_REBOOT_COMPLETED
Message: Device <deviceID> rebooted successfully, and is in ZTP mode
Severity: Info
Explanation: Device rebooted successfully, and is in ZTP mode.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_ENTERZTP_REBOOT_STARTED
Message: Rebooting device <deviceID>
Severity: Info
Explanation: Device is being rebooted.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_EXITZTP_COMPLETED
Message: Device <deviceID> rebooted successfully, is out of ZTP, and back up streaming
Severity: Info

Explanation: ExitZTP completed
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_EXITZTP_DELETE_BANNER
Message: Deleting ZTP login banner on device <deviceID>
Severity: Info
Explanation: Deleting ZTP banner.
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_EXITZTP_DEVICE_NOT_IN_ZTP
Message: Device <deviceID> is already out of ZTP mode before action started
Severity: Info
Explanation: Device already exited ZTP mode
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_EXITZTP_FAILED
Message: <errorMessage>
Severity: Error
Explanation: ExitZTP failed due to some reason
Recommended Action: Automatic retry happens based on the tunables. Probably the second retry might get it fixed. If not, retry ExitZTP after making sure the device is in sane state, please try again. If the problem persists, contact Arista support.
Services: changecontrol

Mnemonic: CC_EXITZTP_RETRY
Message: Retrying ExitZTP in <retryInterval> seconds (<tryCount>/<totalRetryCount>)
Severity: Info
Explanation: ExitZTP is being retried
Recommended Action: No action required
Services: changecontrol

Mnemonic: CC_FAILED
Message: CC <ccName> completed with error: <runError>

Severity: Error

Explanation: CC completed with error

Recommended Action: Take appropriate action using the logs. After fixing them, please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_ABORT_AND_RESTORE

Message: Installation of <imageSwiName> failed: <installationError>. Attempting to restore the previous state.

Severity: Error

Explanation: Image installation failed so reverting to old image

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_COMPLIANCE_CHECK_FAILED

Message: Failed to get image and extension compliance, error: <error>. Please check compliance status.

Severity: Error

Explanation: Couldn't obtain compliance status

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_DEVICE_NOT_COMPLIANT

Message: Device is not in compliance, compliance status: <imageStatus>

Severity: Error

Explanation: Device is not in compliance

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_EXTENSION_INSTALL_FAIL_RESTORE

Message: Failed to install extensions, error: <error>. Trying to restore the original extensions

Severity: Info

Explanation: Failed image extension installation. Restoring old extensions

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_IMAGE_EXTENSION_RESTORE_SUCCESS

Message: Restored original extensions successfully

Severity: Info

Explanation: Restored old extensions.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_INSUFFICIENT_SPACE

Message: Insufficient space on <device/supervisor>

Severity: Info

Explanation: Space available on the device is not enough.

Recommended Action: Cleanup space. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_REBOOT_COMPLETED

Message: Successfully rebooted device <hostName>

Severity: Info

Explanation: ChangeControl Set Image action successfully rebooted the device.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_IMAGE_REBOOT_STARTED

Message: Rebooting the device: <hostName> in reloadMode <reloadMode>

Severity: Info

Explanation: ChangeControl Set Image action is rebooting the device.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_IMAGE_RESTORE_FAILED

Message: Failed to restore the original extensions, error: <error>

Severity: Error

Explanation: Image restoration failed

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_IMAGE_STARTED

Message: Applying <imageSource> at the timestamp <imageTimestamp> on <hostname> with reload mode <reloadMode>

Severity: Info

Explanation: ChangeControl Set Image action started

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_INSUFFICIENT_SPACE_FILES_DELETED

Message: List of files deleted from <device/supervisor>: <deletedFileNames>

Severity: Info

Explanation: Files are deleted to make space for downloading the intended file.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_ACTIVE

Message: MLAG is active, negotiationStatus is "connected", portsErrdisabled is false for device <hostname>

Severity: Info

Explanation: MLAG is active.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_CONFIGSANITY_FAILED

Message: Checking MLAG config-sanity every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Error

Explanation: Unable to check MLAG config sanity

Recommended Action: Ensure MLAG sanity status in syslogs or Arista CLI. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_CONFIG_SANITY_STARTED

Message: Checking MLAG config-sanity for device <hostname> started

Severity: Info

Explanation: Checking MLAG config-sanity started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_CONFIG_SANITY_SUCCEEDED

Message: Checking MLAG config-sanity for device <hostname> succeeded

Severity: Info

Explanation: Checking MLAG config-sanity succeeded.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_DETAIL_FAILED

Message: Getting MLAG detail every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Info

Explanation: Getting MLAG detail failed.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_DUALPRIMARY_FAILED

Message: Checking MLAG dual-primary every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Error

Explanation: Unable to check MLAG dual primary

Recommended Action: Ensure MLAG sanity status in syslogs or Arista CLI. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_DUAL_PRIMARY_STARTED

Message: Checking MLAG dual-primary for device <hostname> started

Severity: Info

Explanation: Checking MLAG dual-primary started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_DUAL_PRIMARY_SUCCEEDED

Message: Checking MLAG dual-primary for device <hostname> succeeded

Severity: Info

Explanation: Checking MLAG dual-primary succeeded.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_ISSU_FAILED

Message: Checking MLAG ISSU warnings every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Error

Explanation: Unable to check ISSU warnings

Recommended Action: Ensure MLAG sanity status in syslogs or Arista CLI. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_ISSU_WARNINGS_STARTED

Message: Checking MLAG ISSU warnings for device <hostname> started

Severity: Info

Explanation: Checking MLAG ISSU warnings started.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_ISSU_WARNINGS_SUCCEEDED

Message: Checking MLAG ISSU warnings for device <hostname> succeeded

Severity: Info

Explanation: Checking MLAG ISSU warnings succeeded.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_SANITY_FAILED

Message: Checking MLAG sanity every <pollInterval>, attempt <attemptNumber> failed, error: <error>

Severity: Error

Explanation: Unable to check MLAG sanity

Recommended Action: Ensure MLAG sanity status in syslogs or Arista CLI. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_MLAGHEALTH_STARTED

Message: Executing <actionName> for device: <hostname>

Severity: Info

Explanation: Executing MLAG health check.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_PEER_SUPERVISOR_FILES_DELETED

Message: List of files deleted from peer supervisor: <deletedFileNames>

Severity: Info

Explanation: Files are deleted to make space for downloading the intended file

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_PRIMARY_SUPERVISOR_FILES_DELETED

Message: List of files deleted from primary supervisor: <deletedFileNames>

Severity: Info

Explanation: Files are deleted to make space for downloading the intended file

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_REBOOT_TIMEDOUT

Message: Device reboot timeout reached for device <deviceID>

Severity: Error

Explanation: Device did not reboot in time

Recommended Action: Check if TerminAttr streaming or any other error. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_INVALID_LANGUAGE

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Script is not written in python2/python3.

Recommended Action: Fix the script. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_PY2_EXECUTION_FAILED

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Script execution failed

Recommended Action: Fix the script. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_PY2_INTERNAL_ERROR

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Python script execution resulted in an internal/infra error

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_PY2_INVALID_RESPONSE

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Didn't recognise the response while running python script.

Recommended Action: Fix the script. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_PY3_EXECUTION_FAILED

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Script execution failed

Recommended Action: Fix the script. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_PY3_INTERNAL_ERROR

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Python script execution resulted in an internal/infra error

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_SCRIPT_PY3_INVALID_RESPONSE

Message: <actionInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Didn't recognise the response while running python script.

Recommended Action: Fix the script. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_STARTED

Message: CC <ccName> started, dispatching action(s) to agent(s)

Severity: Info

Explanation: CC has begun

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TASK_CANCEL

Message: Preemptively canceling task. Could not setup task cancellation.

Severity: Error

Explanation: Canceling task because of internal error

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_TASK_CANCELLED

Message: Cancellation of task completed

Severity: Info

Explanation: Task was cancelled successfully.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TASK_CANCEL_UNEXPECTED_STATE

Message: Cancelling task because it started in an unexpected state. Possibly due to agent restart or prior execution. Task execution can be retried.

Severity: Error

Explanation: Canceling task as it started in an unexpected state

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_TASK_COMPLETED

Message: Action <actionName> Task <taskID> completed successfully

Severity: Info

Explanation: Task has completed

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TASK_CONFIG_PUSH_MGMT_IP_UNCONFIGURED

Message: Configlet push will not be processed. Management IP is not configured, which will make the device unreachable. Ensure that reconcile configlet is present or management IP is present in the applied configlets

Severity: Error

Explanation: Management IP not configured

Recommended Action: Fix the error as suggested in the log. Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_TASK_DECOMMISSION_DEVICE_FAILED

Message: Decommissioning device <deviceID> failed

Severity: Error

Explanation: Device decommissioning failed during Replace device task

Recommended Action: Check if manual decommissioning of the device will do, or please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_TASK_DECOMMISSION_SUCCEEDED

Message: Successfully decommissioned device <deviceID>

Severity: Info

Explanation: Device decommissioning succeeded for Replace device task

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TASK_DECOMMISSION_STARTED

Message: Decommissioning device <deviceID>

Severity: Info

Explanation: Decommissioning of the device has started

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TASK_FAILED

Message: <actionInfo-taskInfo> with ID <stageID> completed with error: <error>

Severity: Error

Explanation: Task has failed

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: changecontrol

Mnemonic: CC_TASK_MGMT_IP_CHANGED

Message: Management IP changed from: <targetIPAddress> to <proposedIPType> address: <proposedIPAddress>

Severity: Info

Explanation: Updated management IP address for device.

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TASK_STARTED

Message: Action <actionName> Task <taskID> started

Severity: Info

Explanation: Task has begun

Recommended Action: No action required

Services: changecontrol

Mnemonic: CC_TA_STATUS_TIMEDOUT

Message: Timeout reached while waiting for TerminAttr to <streamingOrNot> stream on device <deviceID>

Severity: Error

Explanation: Device is either not streaming or still streaming in the expected timeout

Recommended Action: Check TA logs/device console logs or contact Arista support.

Services: changecontrol

Mnemonic: CERT_OCSP_VERIFICATION_FAILURE

Message: <userID> tried to log in to CVP from IP: <IP>. Failed due to OCSP verification failure.

Severity: Warning

Explanation: Failed to login to CVP due to OCSP verification failure

Recommended Action: Please check the OCSP server configuration and try again or check if the client certificate is revoked. If the problem persists, contact Arista support.

Services: aaa

Mnemonic: CV_SSL_CERT_ADDED_IN_TRUSTED_LIST

Message: <certType> created with key: <certKey>

Severity: Info

Explanation: Successfully added the current CloudVision SSL certificate to the trusted certificate list.

Recommended Action: No action required

Services: certs

Mnemonic: CV_SSL_CERT_CSR_CREATED

Message: <certType> created with key: <certKey>

Severity: Info

Explanation: Successfully created the CSR for the current CloudVision SSL certificate.

Recommended Action: No action required

Services: certs

Mnemonic: CV_SSL_CERT_CSR_DELETED

Message: <certType> deleted with key: <certKey>

Severity: Info

Explanation: Successfully deleted the CSR for the current CloudVision SSL certificate.

Recommended Action: No action required

Services: certs

Mnemonic: CV_SSL_CERT_INSTALLATION_FAILED

Message: Action: installCVPCertificate <certType> (<certKey>): <error>

Severity: Error

Explanation: CloudVision SSL certificate installation failed.

Recommended Action: Please verify that you are installing a valid certificate. You can check the error message and then retry to install the certificate. If the problem persists, contact Arista support.

Services: certs

Mnemonic: CV_SSL_CERT_INSTALLED

Message: Action: installCVPCertificate <certType> (<certKey>): <result>

Severity: Info

Explanation: CloudVision SSL certificate installation completed.

Recommended Action: No action required

Services: certs

Mnemonic: CV_SSL_CERT_PREV_CSR_DELETED

Message: <certType> deleted with key: <certKey>

Severity: Info

Explanation: Successfully deleted any CSR for the previous CloudVision SSL certificate.

Recommended Action: No action required

Services: certs

Mnemonic: CV_SSL_CLIENT_CERT_DELETED

Message: <certType> deleted with key: <certKey>

Severity: Info

Explanation: Successfully deleted the CloudVision SSL Client Certificate.

Recommended Action: No action required

Services: certs

Mnemonic: DEFAULT_ROOT_CERT_GENERATED

Message: Successfully generated default root CA certificate

Severity: Info

Explanation: Successfully generated Arista Default Root CA certificate for your CloudVision tenant.

Recommended Action: No action required

Services: devicecertprovisioner

Mnemonic: DEFAULT_ROOT_CERT_GENERATION_FAILED

Message: Failed to generate default root CA certificate

Severity: Error

Explanation: Failed to generate Arista Default Root CA certificate for your CloudVision tenant.

Recommended Action: No action is required from you. Generation of Arista Default Root CA certificate will be retried after 24 hours. If the problem persists after the retry, contact Arista Support.

Services: devicecertprovisioner

Mnemonic: DELETE_RELATION

Message: Entity: <entityID> of EntityType: <entityType>, deleted all relations for subject: <subjectID> of subjectType: <subjectType>, on object: <objectID> of objectType: <objectType>

Severity: Info

Explanation: Deleted access control relations.

Recommended Action: No action required

Services: accesscontrol

Mnemonic: DEVICE_CERT_DELETED

Message: Device certificate <certName> successfully deleted from device <deviceHostname/deviceSerialNumber>

Severity: Info

Explanation: Successfully deleted TLS certificate for STUN authentication from the device.

Recommended Action: No action required

Services: devicecertprovisioner

Mnemonic: DEVICE_CERT_DELETION_FAILED

Message: Failed to delete device certificate <certName> from device <deviceHostname/deviceSerialNumber>

Severity: Error

Explanation: Failed to delete TLS certificate for STUN authentication from the device.

Recommended Action: Ensure that the device is actively streaming. Deletion of the device certificate will be automatically retried after 24 hours. If the problem persists after the retry, contact Arista Support.

Services: devicecertprovisioner

Mnemonic: DEVICE_CERT_INSTALLATION_FAILED

Message: Failed to provision device certificate <certName> for device <deviceHostname/deviceSerialNumber>: <error>

Severity: Error

Explanation: Failed to provision and install TLS certificate for STUN authentication on the device. STUN authentication will fail and connectivity with pathfinder will be impacted.

Recommended Action: Ensure that the device is actively streaming. Provisioning of the device certificate will be automatically retried after 24 hours. If the problem persists after the retry, contact Arista Support.

Services: devicecertprovisioner

Mnemonic: DEVICE_CERT_INSTALLED

Message: Device certificate <certName> successfully provisioned for device <deviceHostname/deviceSerialNumber>

Severity: Info

Explanation: Successfully provisioned and installed TLS certificate for STUN authentication on the device.

Recommended Action: No action required

Services: devicecertprovisioner

Mnemonic: DEVICE_CERT_ROTATED

Message: Device certificate <certName> successfully rotated for device <deviceHostname/deviceSerialNumber>

Severity: Info

Explanation: Successfully rotated TLS certificate for STUN authentication on the device.

Recommended Action: No action required

Services: devicecertprovisioner

Mnemonic: DEVICE_CERT_ROTATION_FAILED

Message: Failed to rotate device certificate <certName> for device <deviceHostname/deviceSerialNumber>: <error>

Severity: Error

Explanation: Failed to rotate TLS certificate for STUN authentication on the device. STUN

authentication might fail and connectivity with Pathfinder might be impacted.

Recommended Action: Ensure that the device is actively streaming. Rotation of the device certificate will be automatically retried after 24 hours. If the problem persists after the retry, contact Arista Support.

Services: devicecertprovisioner

Mnemonic: DEVICE_CONTAINER_MAPPING_SUCCESS

Message: Device <deviceKey> mapped to container <containerName>

Severity: Info

Explanation: Device successfully mapped to container.

Recommended Action: No action required

Services: inventory

Mnemonic: DEVICE_DECOMMISSIONING_SUCCESS

Message: Device decommissioned for the device <deviceId>

Severity: Warning

Explanation: Device successfully decommissioned.

Recommended Action: No action required

Services: inventory

Mnemonic: DEVICE_ONBOARDING_INITIATED

Message: Device onboarding initiated for <host>

Severity: Info

Explanation: Device onboarding has started.

Recommended Action: No action required

Services: inventory

Mnemonic: DEVICE_PROVISIONING_SUCCESS

Message: Successfully provisioned streaming device: <hostNameOrIP>

Severity: Info

Explanation: Device provisioned successfully. It is mapped to the Undefined Container and should be moved to a defined container to allow image/config push.

Recommended Action: No action required

Services: inventory

Mnemonic: DEVICE_UNPROVISIONING_SUCCESS

Message: Device deleted for the device <systemMacAddress>
Severity: Warning
Explanation: Device successfully unprovisioned. It's provisioning data has been purged.
Recommended Action: No action required
Services: inventory

Mnemonic: DEV_MEMBERSHIP_UPDATED
Message: Successfully updated device permissions on tag assignment changes in the workspace: <workspaceID>
Severity: Info
Explanation: Successfully updated device permissions on tag assignment changes.
Recommended Action: No action required
Services: device-rbac

Mnemonic: DEV_MEMBERSHIP_UPDATE_FAILED
Message: Failed to update device permissions on tag assignment changes in the workspace: <workspaceID>
Severity: Critical
Explanation: The update of device permissions due to tag assignment changes failed.
Recommended Action: Re-save the device roles affected by tag assignments in the workspace. The affected roles are found in the Modification Details screen of the workspace.
Services: device-rbac

Mnemonic: FILTER_ADD

Message: Added filter <filterName>

Severity: Info

Explanation: The filter was added.

Recommended Action: No action required

Services: pcm

Mnemonic: FILTER_DELETE

Message: Deleted filter <filterName>

Severity: Info

Explanation: The filter was deleted.

Recommended Action: No action required

Services: pcm

Mnemonic: FILTER_MAP_ADD

Message: Mapped filter <filterName> to tag <label>:<value>

Severity: Info

Explanation: The filter was assigned to a tag which could affect the compliance of some devices.

Recommended Action: No action required

Services: pcm

Mnemonic: FILTER_MAP_DELETE

Message: Deleted filter <filterName> to tag <label>:<value> mapping

Severity: Info

Explanation: The filter was unassigned from a tag which could affect the compliance of some devices.

Recommended Action: No action required

Services: pcm

Mnemonic: IMAGE_ADDED

Message: Image <imageName> added successfully.

Severity: Info

Explanation: Swi or extension added to CloudVision.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_BUNDLE_CREATED

Message: Image bundle <imageBundleName> added successfully.

Severity: Info

Explanation: Image bundle created.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_BUNDLE_DELETED

Message: Image bundle <imageBundleName> deleted successfully.

Severity: Info

Explanation: Image bundle removed from CloudVision.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_BUNDLE_NOTES_UPDATED

Message: Image bundle <imageBundleName> notes updated

Severity: Info

Explanation: Image bundle notes updated.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_BUNDLE_UPDATED

Message: Image bundle <imageBundleName> updated successfully.

Severity: Info

Explanation: The swi or extension in an image bundle updated.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_BUNDLE_UPDATED_AND_TASKS_CREATED

Message: Image bundle <imageBundleName> updated and task creation triggered.

Severity: Info

Explanation: Image bundle updated and tasks created to update devices.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_DELETED

Message: Image <imageID> deleted successfully.

Severity: Info

Explanation: Swi or extension removed from CloudVision.

Recommended Action: No action required

Services: image

Mnemonic: IMAGE_UPDATED

Message: Image <imageName> updated successfully.

Severity: Info

Explanation: Swi or extension updated in CloudVision.

Recommended Action: No action required

Services: image

Mnemonic: INSTALL_LICENSE_CONFIG_DELETED

Message: Install License Config with serial number:[<licenseFileSerialNumber>] is Deleted

Severity: Info

Explanation: Accounting log for license file deletion

Recommended Action: No action required

Services: license

Mnemonic: IPAM_INT_ALLOC_CREATE

Message: Int Allocation of type <reservationType> with value <newAllocationValue> created under <parentID>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_ALLOC_DELETE

Message: IntegerAllocationConfig: IntegerAllocation for Key <integerAllocationKey> deleted

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_ALLOC_UPDATE

Message: Allocation with ID <existingAllocationID> updated

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_NEXT_ALLOC

Message: Int Allocation <allocationID> created under Reservation <reservationName> via Next<objectType>Allocation

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_NEXT_MULTI_ALLOCS_CREATE

Message: Int Allocation <newAllocationID> created under Reservation <parentReservationRange> via NextMultipleAllocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_NEXT_MULTI_ALLOCS_CREATE_SQ

Message: Int Allocation <newAllocationID> created under Reservation <newReservationRange> via Next Multiple Allocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_NEXT_MULTI_ALLOCS_RES_CREATE

Message: Int Reservation <parentReservationID> created under Pool <poolName> via NextMultipleAllocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_NEXT_MULTI_ALLOCS_RES_CREATE_SQ

Message: Reservation with range <newReservationRange> created under pool <poolParentID> via Next Multiple Allocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_NEXT_RES

Message: Int Reservation with range <reservationRange> created under pool <parentID> via Next Reservation

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_RES_CREATE

Message: Reservation with range <rangeStart>|<rangeEnd> created under pool <parentID>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_RES_DELETE

Message: IntegerReservationConfig: IntegerReservation with Key <integerReservationKey> deleted

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_INT_RES_UPDATE

Message: Int Reservation with ID <existingReservationID> updated

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_ALLOC_CREATE

Message: IP Allocation with address <newAllocationAddress> created under <parentID>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_ALLOC_DELETE

Message: IPAllocationConfig: IPAllocation with Key <IPAllocationKey> deleted

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_ALLOC_UPDATE

Message: Allocation with ID <existingAllocationID> updated

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_ALLOC

Message: IP Allocation <allocationID> created under Reservation <reservationName> via Next<objectType>Allocation

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_MULTI_ALLOCS_CREATE

Message: Allocation <newAllocationID> created under Reservation <parentReservationRange> via NextMultipleAllocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_MULTI_ALLOCS_CREATE_SQ

Message: Allocation <newAllocationID> created under Reservation <newReservationRange> via Next Multiple Allocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_MULTI_ALLOCS_RES_CREATE

Message: Reservation <parentReservationID> created under Pool <poolName> via NextMultipleAllocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_MULTI_ALLOCS_RES_CREATE_SQ

Message: IP Reservation with range <reservationRange> created under pool <poolParentID> via Next Multiple Allocations

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_RES

Message: IP Reservation with range <reservationRange> created under pool <parentID> via Next Reservation

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_NEXT_SUBNET

Message: Subnet <subnet> created under parent Subnet <parentID> via Next Subnet

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_RES_CREATE

Message: IP Reservation with range <rangeStart>|<rangeEnd> created under pool <parentID>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_RES_DELETE

Message: IPReservationConfig: IPReservation with Key <IPReservationKey> deleted

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_RES_UPDATE

Message: Reservation with ID <existingReservationID> updated

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_SUBNET_CREATE

Message: Pool with subnet <newSubnet> created under <parentSubnetID>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_SUBNET_DELETE

Message: IPPoolConfig: IPPool/Subnet <IPPoolKey> deleted

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_SUBNET_GATEWAY_ALLOC_CREATE

Message: Gateway allocation <newPoolGateway> created under reservation
<newReservationName>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_IP_SUBNET_GATEWAY_RES_CREATE

Message: Gateway reservation with range <newReservationRange> created under pool
<poolName>

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_NETWORK_CREATE

Message: Network with name <networkID> created

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_NETWORK_DELETE

Message: Network with name <networkID> deleted

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_NETWORK_UPDATE

Message: Network <existingNetworkName> updated

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: IPAM_POOL_UPDATE

Message: Pool with ID <existingPoolID> updated

Severity: Info

Explanation: IPAM accounting message

Recommended Action: No action required

Services: ipam

Mnemonic: LICENSE_ASSIGNED

Message: License with skuID:[<skuID>] is assigned to device:[<deviceSerialNumber>]

Severity: Info

Explanation: License assigned to device successfully.

Recommended Action: No action required

Services: license

Mnemonic: LICENSE_FILE_DELETED

Message: License File with serial number:[<licenseFileSerialNumber>] is Deleted

Severity: Info

Explanation: Accounting log for license file deletion

Recommended Action: No action required

Services: license

Mnemonic: LICENSE_FILE_INSTALLED

Message: License File with serial number:[<licenseFileSerialNumber>] is Installed

Severity: Info

Explanation: Accounting log for license file installation

Recommended Action: No action required

Services: license

Mnemonic: LICENSE_FILE_UPLOAD

Message: License File with serial number:[<licenseFileSerialNumber>] is saved in aries

Severity: Info

Explanation: Accounting log for license file repository

Recommended Action: No action required

Services: license

Mnemonic: LOCATION_ACCESS_POLICY_ADDED

Message: Location access policy has been successfully added for the following subnets:
<subnetIPs>.

Severity: Info

Explanation: Location access policy added successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: LOCATION_ACCESS_POLICY_DELETED

Message: Location access policy has been successfully deleted for entity: <entityName> (Type: <entityType>).

Severity: Info

Explanation: Location access policy deleted successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: LOGIN_FAILURE

Message: <userID> tried to log in to CVP from IP: <IP>. Failed!

Severity: Warning

Explanation: Failed to login to CVP

Recommended Action: Please provide the correct login credentials or if the credentials are correct then please check the SSO configuration. If the problem persists, contact Arista support

Services: aaa

Mnemonic: LOGIN_LIMIT_EXCEEDED_FAILURE

Message: <userID> tried to log in to CVP from IP: <IP>. Failed due to exceeding login limit.

Severity: Warning

Explanation: Failed to login to CVP

Recommended Action: Please logout from other active login sessions. In case the user can't, they should inform Admin to clear out all their sessions. User sessions can be cleared from the 'cv/settings/aaa-users' page on the CV UI.

Services: aaa

Mnemonic: LOGIN_SUCCESS_EXTERNAL_USER

Message: Logged in from IP: <IP> with Authentication: <authenticationType>, Authorization: <authorizationType>, roles received from provider: <roleNames> and current roles: <roleNames>

Severity: Info

Explanation: External (RADIUS/TACACS/LDAP) user logged in successfully

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_SUCCESS_LOCAL_USER

Message: Logged in from IP: <IP> with Authentication: <authenticationType>, Authorization: <authorizationType> and current roles: <roleNames>

Severity: Info

Explanation: LOCAL user logged in successfully

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_BEARER_TOKEN_SUCCESS

Message: Logged in to CV with Bearer Token through <providerID> from IP: <IP>

Severity: Info

Explanation: Successfully logged in to CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_EMAIL_INVITATION_SUCCESS

Message: Logged in from IP: <IP> with Authentication: Email Invitation

Severity: Info

Explanation: Successfully logged in to CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_MOBILE_APP_SUCCESS

Message: Logged in to CV through mobile app from IP: <IP>

Severity: Info

Explanation: Successfully logged in to CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_OIDC_PKCE_SUCCESS

Message: Logged in to CV with OIDC PKCE from IP: <IP>

Severity: Info

Explanation: Successfully logged in to CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_OIDC_SUCCESS

Message: Logged in from IP: <IP> with Authentication: <providerID> and current roles: <roleNames>

Severity: Info

Explanation: Successfully logged in to CloudVision with OIDC provider.

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_OIDC_SUCCESS_MAPPING_ENABLED

Message: Logged in from IP: <IP> with Authentication: <providerID>, roles received from provider: <roleNames> and current roles: <roleNames>

Severity: Info

Explanation: Successfully logged in to CloudVision with OIDC provider.

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_SAML_PKCE_SUCCESS

Message: Logged in to CV with SAML PKCE from IP: <IP>

Severity: Info

Explanation: Successfully logged in to CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_SAML_SUCCESS

Message: Logged in from IP: <IP> with Authentication: <providerID> and current roles: <roleNames>

Severity: Info

Explanation: Successfully logged in to CloudVision with SAML provider.

Recommended Action: No action required

Services: aaa

Mnemonic: LOGIN_WITH_SAML_SUCCESS_MAPPING_ENABLED

Message: Logged in from IP: <IP> with Authentication: <providerID>, roles received from provider: <roleNames> and current roles: <roleNames>

Severity: Info

Explanation: Successfully logged in to CloudVision with SAML provider.

Recommended Action: No action required

Services: aaa

Mnemonic: LOGOUT_FAILURE

Message: Tried to log out of CVP from IP: <IP>. Failed!

Severity: Error

Explanation: Failed to log out of CloudVision

Recommended Action: Please clear the browser cookies before the next login.

Services: aaa

Mnemonic: LOGOUT_SSO_SUCCESS

Message: Logged out of CV from IP: <IP>

Severity: Info

Explanation: Successfully logged out of CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: LOGOUT_SSO_SUCCESS_IDLE_TIMEOUT

Message: Logged out of CV from IP: <IP> due to Idle Timeout

Severity: Info

Explanation: Successfully logged out of CloudVision due to Idle Timeout

Recommended Action: No action required

Services: aaa

Mnemonic: LOGOUT_SUCCESS

Message: Logged out of CVP from IP: <IP>

Severity: Info

Explanation: Successfully logged out of CloudVision

Recommended Action: No action required

Services: aaa

Mnemonic: MOVE_EOS_DEVICE_SERIAL_FAILED

Message: Tenant reassignment for EOS device serial <deviceserial> of sales order number <salesorder> from <sourcetenant> to <destinationtenant> failed, error: <error>

Severity: Info

Explanation: Asset move failed.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: assetmanager

Mnemonic: MOVE_EOS_DEVICE_SERIAL_SUCCEEDED

Message: Tenant reassignment for EOS device serial <deviceserial> of sales order number <salesorder> from <sourcetenant> to <destinationtenant> succeeded

Severity: Info

Explanation: Asset move succeeded.

Recommended Action: No action required

Services: assetmanager

Mnemonic: MOVE_LICENSE_FAILED

Message: Tenant reassignment for license <licenseuuid> of sales order number <salesorder> from <sourcetenant> to <destinationtenant> failed, error: <error>

Severity: Info

Explanation: Asset move failed.

Recommended Action: Please try again. If the problem persists, contact Arista support.

Services: assetmanager

Mnemonic: MOVE_LICENSE_SUCCEEDED

Message: Tenant reassignment for license <licenseuuid> of sales order number <salesorder> from <sourcetenant> to <destinationtenant> succeeded

Severity: Info

Explanation: Asset move succeeded.

Recommended Action: No action required

Services: assetmanager

Mnemonic: MSS_POLICY_ADD

Message: Policy "<policyName>" added.

Severity: Info

Explanation: New policy was added.

Recommended Action: No action required

Services: mssmonitor

Mnemonic: MSS_POLICY_DELETE
Message: Policy "<policyName>" deleted.
Severity: Info
Explanation: Policy was deleted.
Recommended Action: No action required
Services: mssmonitor

Mnemonic: MSS_POLICY_UPDATE
Message: Policy "<policyName>" updated.
Severity: Info
Explanation: Policy was updated.
Recommended Action: No action required
Services: mssmonitor

Mnemonic: MSS_RULES_ADD
Message: Rule "<ruleName>" added to policy "<policyName>".
Severity: Info
Explanation: New rule was added.
Recommended Action: No action required
Services: mssmonitor

Mnemonic: MSS_RULES_DELETE
Message: Rule "<ruleName>" of policy "<policyName>" deleted.
Severity: Info
Explanation: Rule was deleted.
Recommended Action: No action required
Services: mssmonitor

Mnemonic: MSS_RULES_UPDATE
Message: Rule "<ruleName>" of policy "<policyName>" updated.
Severity: Info
Explanation: Rule was updated.
Recommended Action: No action required
Services: mssmonitor

Mnemonic: MSS_SECURITY_DOMAIN_ADD

Message: SecurityDomain "<sdName>" added.

Severity: Info

Explanation: New SecurityDomain was added.

Recommended Action: No action required

Services: mssmonitor

Mnemonic: MSS_SECURITY_DOMAIN_DELETE

Message: SecurityDomain "<sdName>" deleted.

Severity: Info

Explanation: SecurityDomain was deleted.

Recommended Action: No action required

Services: mssmonitor

Mnemonic: OAUTH_PROVIDER_ADDED

Message: OAuth provider <providerID> successfully added

Severity: Info

Explanation: OAuth provider added successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: OAUTH_PROVIDER_DELETED

Message: OAuth provider <providerID> successfully deleted

Severity: Info

Explanation: OAuth provider deleted successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: PASSWORD_POLICY_UPDATED

Message: Password policy successfully updated by user: <userName> to: <updatedSettings>

Severity: Info

Explanation: Password policy updated successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: PREV_CV_SSL_CERT_DELETED

Message: <certType> deleted with key: <certKey>

Severity: Info

Explanation: Successfully deleted the previous CloudVision SSL certificate.

Recommended Action: No action required

Services: certs

Mnemonic: PWD_CHANGE_FAILURE

Message: <userName> tried to change password from IP: <IP>. Failed!

Severity: Warning

Explanation: Failed to change user's own password.

Recommended Action: Please try again after sometime. If the problem persists, contact Arista support.

Services: aaa

Mnemonic: PWD_CHANGE_SUCCESS

Message: <userName> successfully changed password from IP: <IP>

Severity: Info

Explanation: Password changed successfully

Recommended Action: No action required

Services: aaa

Mnemonic: ROLES_DELETED
Message: Roles deleted: <roleNames>
Severity: Info
Explanation: Roles deleted successfully.
Recommended Action: No action required
Services: user, role

Mnemonic: ROLE_CREATED
Message: Role <roleName> created
Severity: Info
Explanation: Role created successfully.
Recommended Action: No action required
Services: user, role

Mnemonic: ROLE_DEV_PERM_DELETED
Message: Successfully deleted device permissions for role <roleName>
Severity: Info
Explanation: Successfully deleted device permissions for the role
Recommended Action: No action required
Services: device-rbac

Mnemonic: ROLE_DEV_PERM_DELETE_FAILED
Message: Failed to delete device permission for role <roleName>.
Severity: Critical
Explanation: Delete of device permissions for a role failed.
Recommended Action: Try deleting device permissions for the role again
Services: device-rbac

Mnemonic: ROLE_DEV_PERM_UPDATED
Message: Successfully updated device permissions for role <roleName>
Severity: Info
Explanation: Successfully updated device permissions for the role.
Recommended Action: No action required
Services: device-rbac

Mnemonic: ROLE_DEV_PERM_UPDATE_FAILED

Message: Failed to update or create device permission for role <roleName>.

Severity: Critical

Explanation: Update of device permissions for a role failed.

Recommended Action: Try updating the role again

Services: device-rbac

Mnemonic: ROLE_UPDATED

Message: Role <roleName> is updated: <updateDescription>

Severity: Info

Explanation: Role updated successfully.

Recommended Action: No action required

Services: user, role

Mnemonic: SAML_PROVIDER_ADDED
Message: SAML provider <providerID> successfully added
Severity: Info
Explanation: SAML provider added successfully.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: SAML_PROVIDER_DELETED
Message: SAML provider <providerID> successfully deleted
Severity: Info
Explanation: SAML provider deleted successfully.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: SERVICE_ACCOUNT_CREATED
Message: Service account created: <acctID>
Severity: Info
Explanation: Service account created successfully.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: SERVICE_ACCOUNT_DELETED
Message: Service account deleted: <acctID>
Severity: Info
Explanation: Service account deleted successfully.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: SERVICE_ACCOUNT_ROLES_UPDATED
Message: Role(s) for service account <acctID> updated to: <roleNames>
Severity: Info
Explanation: Role(s) added/updated to service account successfully.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: SERVICE_ACCOUNT_TOKEN_CREATED

Message: Token <tokenID> created successfully for service account <accountID>

Severity: Info

Explanation: Service account token created successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: SERVICE_ACCOUNT_TOKEN_DELETED

Message: Token <tokenID> deleted successfully for service account <accountID>

Severity: Info

Explanation: Service account token deleted successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: SERVICE_ACCOUNT_TOKEN_REFRESHED

Message: Token <oldTokenID> refreshed to Token <newTokenID> for service account <accountID>

Severity: Info

Explanation: Service account token refreshed successfully

Recommended Action: No action required

Services:

Mnemonic: SERVICE_ACCOUNT_UPDATED

Message: Service account updated: <acctID>

Severity: Info

Explanation: Service account updated successfully.

Recommended Action: No action required

Services: admin-aaa

Mnemonic: SSO_LOGIN_LOGOUT_FAILURE

Message: Tried to <action> CV <providerInfo> from IP: <IP>. Failed!: <error>

Severity: Warning

Explanation: Failed to perform login/logout of CloudVision

Recommended Action: Please provide the correct login credentials or if the credentials are correct then please check the SSO configuration. If the problem persists, contact Arista support.

Services: aaa

Mnemonic: SSO_UNKNOWN_USER_LOGIN_LOGOUT_FAILURE

Message: <userName> a user yet to be determined tried to <action> CV from IP: <IP>. Failed!: <error>

Severity: Warning

Explanation: Failed to perform login/logout of CloudVision

Recommended Action: Please provide the correct login credentials or if the credentials are correct then please check the SSO configuration. If the problem persists, contact Arista support.

Services: aaa

Mnemonic: USERS_DELETED
Message: Users deleted: <userIDs>
Severity: Info
Explanation: Users deleted successfully.
Recommended Action: No action required
Services: aaa, user

Mnemonic: USER_CREATED
Message: User created: <userID>
Severity: Info
Explanation: User created successfully.
Recommended Action: No action required
Services: aaa, user

Mnemonic: USER_LOCKED
Message: <userName> tried to log in to CVP from IP: <IP>. Failed! User has been locked out due to consecutive incorrect login attempts for <lockedOutDuration>
Severity: Info
Explanation: A user has been locked out due to consecutive incorrect login attempts.
Recommended Action: No action required
Services: aaa

Mnemonic: USER_LOCKOUT_CONFIG_UPDATED
Message: User Lockout config updated by user <userName> to <configDetails>
Severity: Info
Explanation: User Lockout Config for consecutive incorrect login attempts to CloudVision has been updated.
Recommended Action: No action required
Services: admin-aaa

Mnemonic: USER_ROLES_UPDATED
Message: Roles added to user <userID> : <roleNames>
Severity: Info
Explanation: Roles added to user successfully.
Recommended Action: No action required
Services: aaa, user

Mnemonic: USER_ROLE_ADDED

Message: User <updatedByUserName> assigned role <roleName> to user <userName>

Severity: Info

Explanation: Role assigned to user successfully.

Recommended Action: No action required

Services: aaa, user, role

Mnemonic: USER_ROLE_REMOVED

Message: Role <roleName> removed from user <userName>

Severity: Info

Explanation: Role removed from user successfully.

Recommended Action: No action required

Services: aaa, user, role

Mnemonic: USER_STATUS_UPDATED

Message: User Status <userStatus>

Severity: Info

Explanation: User status updated successfully.

Recommended Action: No action required

Services: aaa, user

Mnemonic: USER_UNLOCKED

Message: Users: [<userNames>] have been unlocked by: <adminName>

Severity: Info

Explanation: Users who got locked out due to consecutive incorrect login attempts have been unlocked by admin.

Recommended Action: No action required

Services: aaa

Mnemonic: USER_UPDATED

Message: User updated: <userName>

Severity: Info

Explanation: User updated successfully.

Recommended Action: No action required

Services: aaa, user

Mnemonic: USER_UPDATE_FAILURE

Message: Could not update the user <userID>, error: <error>

Severity: Error

Explanation: Failed to update user's roles.

Recommended Action: Please check the value of entered parameters or acting user's permissions. If the problem persists, contact Arista support

Services: aaa